



MODEL		NovoCast NC1000
BYOD	BYOD - Supported OS	Windows 7 / 8 / 10 (32 bits and 64 bits), macOS 10.7 and above, iOS 11.0 and above, Android 5.0 and above
		Screen Mirroring for iOS and Android
		Miracast not supported
	Split Screen	1 or 4
	Simultaneous Connections	Up to 40
	Mirroring Resolution	Up to 1080p, 30 fps
	Output Resolution	1080p (1920 x 1080), 720p (1280 x 720)
FEATURES	Collaboration	Windows 10 Extended Desktop function, Moderator function, AirNote for instant annotation from meeting participants, Novo Screennote for virtual whiteboard
	Productivity	QR Code connection support, PIN connection function
	Digital Signage Announcement Board	NA
	Wireless Screen Duplication	NA
	Security	Dual network WiFi & LAN, AES-256 encryption, Kensington lock
CONNECTIVITY	WiFi	802.11ac, b/g/n, 2.4GHz & 5GHz 1T1R with 1 external antenna
	Output	HDMI-Out Audio-Out (3.5mm jack)
	Input	USB Type A; microSD Slot; DC Jack Power-In
SYSTEM	CPU	Quad-core ARM
	Storage	8GB
GENERAL	Power	Input to AC adapter: AC 100-240V, 50/60Hz. Output from AC adapter: 5V/2A. Consumption: 10W
	Product Dimensions (L x W x H)	100 x 100 x 20 mm
	Weight (Net)	184 g
	What's Included	Main Unit, Antenna, HDMI Cable, USB Cable, Power Adapter, USB to Ethernet Adapter, Wall Mount KIT, Document KIT
	Optional Accessory	LauncherPlus (Moderator Mode) (SW requirement: Full version)
	Warranty	3 Years

v05t.p0